



# Demo Board 3991.31.1

## Wide Input Linear Voltage Regulator

### **LDI55-ADEEN**

Low Dropout | Adjustable | Enable Function

For Battery Powered Devices


## 1. Description

This board is used to demonstrate the functionality of the LDI55-ADEEN linear regulator. It has wide input range up to 50V, low-dropout (LDO) voltage regulators with enable function and provides up to 1A of output current. Only two small ceramic capacitors are needed to implement the linear regulator solution. The features of low quiescent current as low as 3  $\mu$ A to 5  $\mu$ A and almost 0.5  $\mu$ A disable current is ideal for powering the battery equipment to a longer service. Simple device measurements such as line and load regulation, dropout, can be demonstrated with just a single voltage source, a voltmeter, an ammeter, and load resistor.


## 2. Features

- Input voltage range up to 50V
- Output current 1A
- Adjustable output voltage
- Low dropout voltage
- Integrated heat pad-low R<sub>th</sub>
- Thermal overload protection
- Short circuit protection function

## 3. Evaluation Board Hardware and Schematic



## 4. PCB View




## 5. Test Points

| Test point/<br>Pin name | Signal         | Comment (expected waveforms or voltage levels on test points) |
|-------------------------|----------------|---------------------------------------------------------------|
| VOUT                    | Output voltage | Adjustable                                                    |
| GND                     | Ground         | Ground                                                        |
| EN                      | Enable         | Enable control input                                          |
| VIN                     | Input voltage  | Input voltage range = up to 50V                               |

## 6. Operation

EVALUATION BOARD CONFIGURATIONS - How to measure the output voltage




Use the following steps to connect the evaluation board to a voltage source and voltmeter:

1. Connect the negative terminal (–) of the voltage source to one of the GND terminal on the evaluation board
2. Connect the positive terminal (+) of the voltage source to the VIN terminal on the evaluation board
3. Connect a load between the VOUT terminal and GND terminal
4. Connect the negative terminal (–) of the voltmeter to GND terminal
5. Connect the positive terminal (+) on the voltmeter to the VOUT terminal.

## APPLICATION NOTE DEMO BOARD 3991.31.1 WIDE INPUT LINEAR VOLTAGE REGULATOR

### EVALUATION BOARD CONFIGURATIONS - How to measure the output current



Use the following steps to connect the evaluation boards to a voltage source and an ampere meter:

1. Connect the positive terminal (+) of the voltage source to the VIN terminal on the evaluation board
2. Connect the positive terminal (+) of the ammeter VIN terminal of the evaluation board
3. Connect the negative terminal (–) of the ammeter to the GND terminal (–)
4. Connect a load between the positive terminal (+) of the ammeter and the VOUT terminal of the evaluation board

## Disclaimer

This demo board application note describes device and circuit proposals and shall not be considered as assured and proven solution for any application. No warranty or guarantee, expressed or implied is made regarding the capacity, performance or suitability of any device, circuit etc.

**Don't hesitate to contact us for further questions:**

[technicalsupport@diotec.com](mailto:technicalsupport@diotec.com)

**Datasheets of all mentioned products can be found at [www.diotec.com](http://www.diotec.com)**

## All rights reserved

The information presented in our data sheets and other documents is to the best of our knowledge true and accurate. It describes the type of component or application and shall not be considered as assured characteristics. No warranty or guarantee, expressed or implied is made regarding the capacity, delivery, performance or suitability of any product or circuit etc, neither does it convey any license under the patent rights of others.

Diotec reserves the right to make changes without further notice. However, regular updating of all product information is provided on our website <sup>1)</sup>. All Diotec products are sold and shipped subject to our "Standard Terms and Conditions of Business" <sup>2)</sup>. The reproduction of all documents is prohibited without the expressed written permission of Diotec Semiconductor AG's Managing Board.

## Disclaimer

1. All products described or contained are designed and intended for use in standard applications, so called commercial/industrial grade, requiring an ordinary level of reliability.

2. Some products are available with the special grades "AEC-Q101 compliant" respectively "AEC-Q101 qualified". These are automotive standards <sup>3)</sup>.

3. Customers using these parts in applications requiring a special or specific grade of quality or reliability, such as (but not limited to) life supporting devices or systems, where failure or malfunction of the product may directly affect human life or health, are obliged to validate whether the use in such cases is appropriate.

Diotec does not assume any liability arising out of such applications or uses of its products. Usage in all such cases is on the own and sole risk of the customer.

4. Although Diotec continuously enhances the quality and reliability of its products, customers must incorporate sufficient safety measures in their designs, such as redundancy, fire containment, and anti-failure, so that personal injury, fire or environmental damage can be prevented. Diotec excludes explicitly every implied warranty or liability regarding the fitness of the products to any other than standard applications.

5. All information described or contained herein are subject to change without notice. Please contact Diotec to obtain the latest information before incorporating Diotec products into any design.

6. All information described and contained herein are intended only to enable the buyer to order Diotec's products. The information must not be used for any other purpose.

7. In the event that any product described or contained herein falls under the category of strategic products controlled by the German Federal Office of Economics and Export Control, this product must not be exported without obtaining an export license from the German Federal Ministry for Economic Affairs and Climate Action in accordance with the valid laws.

## Alle Rechte vorbehalten

Die Angaben in unseren Datenblättern und sonstigen Dokumenten sind nach bestem Wissen und Gewissen gemacht. Sie dienen jedoch allein der Beschreibung und sind nicht als zugesagte Eigenschaften im Rechts-Sinne zu verstehen. Es wird keine Gewähr bezüglich Liefermöglichkeit, Ausführung oder Einsatzmöglichkeit der Bauelemente übernommen, noch dass die angegebenen Bauelemente, Baugruppen, Schaltungen etc. frei von Schutzrechten sind.

Wir behalten uns Änderungen der aufgeführten Daten ohne vorherige Ankündigung vor. Alle Änderungen werden jedoch regelmäßig auf unserer Internet-Seite veröffentlicht <sup>1)</sup>. Verkauf und Lieferung von Diotec-Produkten erfolgt gemäß unseren "Allgemeinen Geschäftsbedingungen" <sup>2)</sup>. Die Vervielfältigung aller Dokumente ist nur mit schriftlicher Genehmigung des Vorstandes der Diotec Semiconductor AG gestattet.

## Haftungsausschluss

1. Alle beschriebenen oder enthaltenen Produkte sind für den Gebrauch in Standardanwendungen mit einem gewöhnlichen Zuverlässigkeitsniveau entworfen und bestimmt, bekannt als kommerziell/industrielle Anwendungen.

2. Einige Produkte sind mit den speziellen Qualifikationen „AEC-Q101 konform“ oder „AEC-Q101 qualifiziert“ erhältlich. Dies sind Automotive-Standards <sup>3)</sup>.

3. Falls diese Produkte in Anwendungen verwendet werden sollen, die einen besonderen Grad der Qualität oder Zuverlässigkeit erfordern, z. B. (aber nicht begrenzt auf) lebenserhaltende Geräte oder Systeme, bei denen durch Ausfall oder eine Störung des Produktes menschliches Leben oder Gesundheit direkt beeinflusst werden kann, ist der Anwender verpflichtet sicherzustellen, dass der beabsichtigte Gebrauch des vorgesehenen Produktes unbedenklich ist.

Diotec übernimmt keine Haftung die sich aus solchen Anwendungen oder der Verwendung der Produkte ergibt. Der Gebrauch für alle solche Anwendungen erfolgt auf eigenes und ausschließliches Risiko des Anwenders.

4. Obwohl Diotec die Qualität und die Zuverlässigkeit seiner Produkte beständig erhöht, müssen Kunden ausreichende Sicherheitsvorkehrungen in ihren Designs vornehmen – wie Redundanz, Feuereindämmung und Ausfallschutz – damit Personenschäden, Feuer oder Umweltschädigung verhindert werden können. Diotec schließt ausdrücklich jede implizierte Garantie oder Verbindlichkeit aus, welche die Eignung der Produkte zu irgendwelchen anderen als Standardanwendungen betrifft.

5. Alle Informationen, die hier beschrieben oder enthalten sind, können jederzeit ohne jede Benachrichtigung geändert werden. Vor Einsatz eines Diotec Produktes in irgendeiner Anwendung sind bei Diotec die neuesten Informationen einzuholen.

6. Alle Informationen, die hier beschrieben oder enthalten sind, sollen dem Kunden nur ermöglichen, Diotec Produkte zu bestellen. Die Informationen dürfen zu keinem anderen Zweck verwendet werden.

7. Sollte ein hier beschriebenes oder enthaltenes Produkt unter Beschränkungen fallen, die durch das deutsche Bundesamt für Wirtschaft und Ausfuhrkontrolle geregelt werden, darf dieses Produkt in Übereinstimmung mit den gültigen Gesetzen nicht ohne Exportgenehmigung vom deutschen Bundesministerium für Wirtschaft und Klimaschutz exportiert werden.

1 Refer to <http://diotec.com/> "Products/Product Changes" respectively "News/Datasheets"  
Siehe <http://diotec.com/> „Produkte/Produktänderungen“ bzw. „News/Datenblätter“

2 Refer data book or <http://diotec.com/> "Company" – Siehe Datenbuch oder <http://diotec.com/> „Unternehmen“

3 Refer to <http://diotec.com/> "Products/Information/Qualification/Commercial Grade and AEC-Q101"  
Siehe <http://diotec.com/> „Produkte/Informationen/Qualifizierung/Standard und AEC-Q101“